MP2341

High-Efficiency, 2A, 24V, 1MHz, Synchronous, Step-Down LED Driver in SOT583 Package

DESCRIPTION

The MP2341 is a 24V, monolithic, synchronous, rectified, step-down, switch-mode white LED driver with built-in internal power MOSFETs and a synchronous rectifier switch. The MP2341 achieves up to 2A of continuous output current with excellent load and line regulation.

Peak current mode control operation provides fast transient response, easy loop design, and tight output regulation.

Fault condition protection includes cycle-by-cycle peak current limiting, output short circuit protection, open LED protection, and thermal shutdown.

The MP2341 requires a minimal number of readily available, standard external components, and is available in a space-saving SOT583 package.

FEATURES

- Wide 4.2V to 24V Operating Input Range
- 125mΩ/75mΩ Low-$R_{DS(ON)}$ Internal Power MOSFETs
- High-Efficiency Synchronous Mode Operation
- Forced PWM Mode
- Fast Load Transient Response
- 1MHz Switching Frequency
- Internal Soft Start (SS)
- Analog Dimming by the DC Voltage through the EN/DIM Pin
- Analog Dimming by the PWM Signal through the PDIM Pin
- PWM Dimming by the PWM Signal through the EN/DIM Pin
- 50:1 Dimming Ratio via Analog Dimming
- 1000:1 Dimming Ratio via PWM Dimming
- Open LED Protection
- Over-Current Protection (OCP) and Hiccup Mode
- Over-Voltage Protection (OVP) with Auto-Recovery
- Thermal Shutdown
- 100mV Feedback (FB) Voltage
- Available in a SOT583 Package

MPL Optimized Performance with MPS Inductor MPL-AL6060 Series

APPLICATIONS

- Infrared LED Drivers
- General LED Drivers
- Flashlights
- Handheld Computer Backlighting

All MPS parts are lead-free, halogen-free, and adhere to the RoHS directive. For MPS green status, please visit the MPS website under Quality Assurance. "MPS", the MPS logo, and "Simple, Easy Solutions" are trademarks of Monolithic Power Systems, Inc. or its subsidiaries.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

TYPICAL APPLICATION



Efficiency vs. V_{IN}

2 WLEDs in series, V_{OUT} = 5.9V, L = 6.5µH, I_{LED} = 2A



MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

ORDERING INFORMATION

Part Number*	Package	Top Marking	MSL Rating
MP2341GTL	SOT583	*See Below*	1

*For Tape & Reel, add suffix –Z (e.g. MP2341GTL-Z).

TOP MARKING

BCEY

LLL

BCE: Product code of MP2341GTL
Y: Year code
LLL: Lot number

PACKAGE REFERENCE



MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

PIN FUNCTIONS

Pin #	Name	Description
1	PDIM	**PWM signal input.** Apply a PWM signal on this pin for brightness control. It is recommended for the dimming frequency to be no lower than 10kHz.
2	VIN	**Supply voltage.** The MP2341 operates on a 4.2V to 24V input rail. A capacitor (C1) is required to decouple the input rail. Connect VIN to the input power supply positive terminal using a wide PCB trace.
3	SW	**Switch output.** Connect SW to the inductor using a wide PCB trace.
4	GND	**System ground.** This is the reference ground of the regulated output voltage. It requires extra care during PCB layout. Use copper traces and vias to connect to GND.
5	BST	**Bootstrap.** Connect a capacitor and a resistor between SW and BST to form a floating supply across the high-side (HS) switch driver. Use a 1µF BST capacitor.
6	EN/DIM	**On/off control input and dimming command input.** Leaving EN/DIM floating or applying a voltage higher than V_{EN_ON} on this pin turns on the chip. For analog dimming, the EN/DIM voltage rises from V_{ADIM_MIN} to V_{ADIM_MAX}, and the output current changes from the minimum value to the full-scale LED current. To apply PWM dimming, apply 100Hz to 2kHz PWM signal with an amplitude above 1.6V to this pin.
7	VCC	**Internal bias supply.** Decouple with a 0.1µF to 0.22µF capacitor. Select a capacitor that does not exceed 0.22µF. The VCC capacitor should be placed as close as possible to the VCC and GND pins.
8	FB	**Current-sense feedback voltage.** FB's internal reference voltage is 0.1V.

ABSOLUTE MAX RATINGS (1)

V_{IN} ..... -0.3V to +26V
V_{SW} ..... -0.3V (-6.5V for < +10ns) to +26V (28V for <10ns)
V_{BST} ..... V_{SW} + 5V
V_{EN} ..... -0.3V to +5V
All other pins ..... -0.3V to +4V
Continuous power dissipation (T_A = 25°C) (2)(4) 2.2W
Junction temperature .....150°C
Lead temperature ..... 260°C
Storage temperature ..... -65°C to +150°C

ESD Ratings

Human body model (HBM)..... ±2000V
Charged device model (CDM)..... ±1250V

Recommended Operating Conditions (3)

Supply voltage (V_{IN}) .....4.2V to 24V
Output voltage (V_{OUT}) ..... 0.8V to 0.9V_{IN} or 20V max
Operating junction temp (T_J)...-40°C to +125°C

Thermal Resistance θ_{JA} θ_{JC}

SOT583

EV2341-TL-00A (4) ..... 55..... 21...°C/W
JESD51-7 (5) ..... 130.... 60...°C/W

Notes:

1) Exceeding these ratings may damage the device.
2) The max allowable power dissipation is a function of the max junction temperature T_J (MAX), the junction-to-ambient thermal resistance θ_{JA}, and the ambient temperature T_A. The max allowable continuous power dissipation at any ambient temperature is calculated by P_D (MAX) = (T_J (MAX) - T_A) / θ_{JA}. Exceeding the max allowable power dissipation can cause excessive die temperature, and the regulator may go into thermal shutdown. Internal thermal shutdown circuitry protects the device from permanent damage.
3) The device is not guaranteed to function outside of its operating conditions.
4) Measured on EV2341-TL-00A, 2-layer PCB, 46mmx46mm.
5) The value of θ_{JA} given in this table is only valid for comparison with other packages and cannot be used for design purposes. These values were calculated in accordance with JESD51-7, and simulated on a specified JEDEC board. They do not represent the performance obtained in an actual application.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

ELECTRICAL CHARACTERISTICS

V_{IN} = 12V, T_J = -40°C to +125°C (6), typical value is tested at T_J = 25°C, unless otherwise noted.

Parameter	Symbol	Condition	Min	Typ	Max	Units
Shutdown supply current	I_{IN}	V_{EN} = 0V			25	μA
Quiescent supply current	I_Q	V_{EN} = 2V, V_{FB} = 1V		500	650	μA
High-side (HS) switch on resistance	HS_{RDS-ON}	V_{BST-SW} = 3.6V		125		mΩ
Low-side (LS) switch on resistance	LS_{RDS-ON}	V_{CC} = 3.6V		75		mΩ
Switch leakage	SW_{LKG}	V_{EN} = 0V, V_{SW} = 12V			1	μA
HS switch over-current protection (OCP) current limit	$I_{LIMIT_HS_OC}$		3.4	4		A
LS switch OCP current limit	$I_{LIMIT_LS_OC}$			3		A
LS current in continuous conduction mode (CCM)				-1.5		A
Oscillator frequency	f_{SW}	V_{FB} = 80mV	0.8	1	1.2	1MHz
Minimum on time (7)	t_{ON_MIN}			60		ns
Minimum off time	t_{OFF_MIN}			160		ns
FB voltage	V_{REF}	EN = 2V, PDIM = high, T_J = 25°C	97.5	100	102.5	mV
FB current	I_{FB}	V_{FB} = 150mV		10	100	nA
Burst mode allowable threshold	$V_{FB_BURST_TH}$			120	145	mV
Burst mode recovery hysteresis	$V_{FB_BURST_HYS}$			20		mV
Hiccup off time				2.4		ms
Enable and Dimming						
EN/DIM off threshold	V_{EN_OFF}	$V_{EN/DIM}$ falling edge	0.27	0.33	0.37	V
EN/DIM on threshold	V_{EN_ON}	$V_{EN/DIM}$ rising edge		0.76		V
Turn-on delay time (7)	t_{ON_DELAY}	From EN high to when I_{LED} starts ramp up		750		μs
Turn-off delay time	t_{OFF_DELAY}			16		ms
EN/DIM pull-up current	$I_{EN/DIM}$	V_{EN} = 0V	4	9	14	μA
Maximum analog dimming threshold	V_{ADIM_MAX}	Theoretically, V_{FB} = 100mV	1.31	1.44	1.57	V
Minimum analog dimming threshold	V_{ADIM_MIN}	V_{FB} = 5mV, T_J = 25°C	0.66	0.74	0.82	V
PDIM						
PDIM input low threshold	V_{PDIM_LO}	V_{PWM} falling			0.4	V
PDIM input high threshold	V_{PDIM_HI}	V_{PWM} rising	1.5			V

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

ELECTRICAL CHARACTERISTICS *(continued)*

V_{IN} = 12V, T_J = -40°C to +125°C [6], typical value is tested at T_J = 25°C, unless otherwise noted.

Parameter	Symbol	Condition	Min	Typ	Max	Units
PDIM pull-up current	I_{PDIM_UP}			1.7		μA
V_{IN} under-voltage lockout (UVLO) rising threshold	$INUV_{VTH}$		3.7	4	4.2	V
V_{IN} UVLO threshold hysteresis	$INUV_{HYS}$			350		mV
Soft-start (SS) time	t_{SS}	LED load = 5.9V/2A, t_{SS} from 0V to 5.9V	0.4	0.56	0.72	ms
VCC voltage	V_{CC}			3.6		V
VCC load regulation		I_{CC} = 5mA		3		%
Thermal shutdown [7]				150		°C
Thermal hysteresis [7]				20		°C

Notes:

6) Not tested in production. Guaranteed by over-temperature correlation.
7) Guaranteed by design and engineering sample characterization.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

TYPICAL PERFORMANCE CHARACTERISTICS

V_{IN} = 12V, 2 WLEDs in series, V_{OUT} = 5.9V, L = 6.5μH, T_A = 25°C, unless otherwise noted.

Enabled Supply Current vs. Input Voltage

$V_{EN/DIM}$ = 2V, V_{FB} = 200mV



Disabled Supply Current vs. Input Voltage

$V_{EN/DIM}$ = 0V



Efficiency vs. V_{IN}

V_{OUT} = 5.9V



Efficiency vs. V_{OUT}

1 to 9 I_R LEDs in series, I_{LED} = 500mA, L = 10μH



Line Regulation

V_{OUT} = 5.9V



Load Regulation

1 to 9 I_R LEDs in series, I_{LED} = 500mA, L = 10μH



MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

TYPICAL PERFORMANCE CHARACTERISTICS *(continued)*

V_{IN} = 12V, 2 WLEDs in series, V_{OUT} = 5.9V, L = 6.5μH, T_A = 25°C, unless otherwise noted.

Analog Dimming Curve
Ramp up/down EN/DIM voltage



Analog Dimming Curve
PDIM frequency = 20kHz



PWM Dimming Curve
EN/DIM frequency = 200Hz



Thermal Test
V_{OUT} = 5.9V



MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

TYPICAL PERFORMANCE CHARACTERISTICS *(continued)*

V_{IN} = 12V, 2 WLEDs in series, V_{OUT} = 5.9V, L = 6.5μH, T_A = 25°C, unless otherwise noted.

Steady State



1μs/div.

VIN Start-Up



1ms/div.

VIN Shutdown



1ms/div.

EN Start-Up



500μs/div.

EN Shutdown



2μs/div.

Minimum Analog Dimming

VPDIM = 2V, frequency = 20kHz,
duty = 0.63%, V_{FB} = 1mV



10μs/div.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

TYPICAL PERFORMANCE CHARACTERISTICS *(continued)*

V_{IN} = 12V, 2 WLEDs in series, V_{OUT} = 5.9V, L = 6.5µH, T_A = 25°C, unless otherwise noted.

PWM Dimming

VEN/DIM = 2V, frequency = 1kHz, duty = 50%



500µs/div.

Open LED Protection



1µs/div.

LED+ to LED- Short Protection



20µs/div.

LED+ to GND Short Protection



2ms/div.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

FUNCTIONAL BLOCK DIAGRAM



Figure 1: Functional Block Diagram

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

OPERATION

The MP2341 is a high-frequency, synchronous, rectified, step-down, switch-mode LED driver with built-in internal power MOSFETs and a synchronous rectifier switch. The MP2341 offers a high-performance solution by achieving up to 2A of continuous output LED current, with excellent load and line regulation over a wide input voltage range.

The MP2341 operates in peak current control mode at a fixed 1MHz frequency to regulate the output current. An internal clock initiates the beginning of every new switching cycle. The integrated high-side power MOSFET (HS-FET) turns on, and the inductor current rises linearly to provide energy to the load. The HS-FET remains on until its current reaches the COMP level value — the output of the internal error amplifier (EA). The error amplifier's output voltage depends on the difference between the output feedback (FB) and the internal high-precision reference. The result of these values determines the amount of energy transferred to the load.

The HS-FET remains off until the next clock cycle begins. When the HS-FET turns off, the low-side MOSFET (LS-FET) turns on and the inductor current flows through the LS-FET. A dead time is inserted to prevent shoot-through by prohibiting the HS-FET and the LS-FET from turning on at the same time.

When the duty cycle of one switching period reaches 84% of the max duty cycle, the current in the HS-FET does not reach the COMP-set current value, and the HS-FET is forced to turn off.

Under-Voltage Lockout (UVLO) and IC Start-Up and Shutdown Procedure

Under-voltage lockout (UVLO) prevents the MP2341 from operating at an insufficient supply voltage. The MP2341's UVLO comparator monitors the output voltage of the internal regulator, which is supplied from V_{IN}.

The MP2341 starts up if both V_{IN} and EN/DIM exceed their respective thresholds. First the reference block starts generating stable reference voltages and currents, and then the internal regulator is enabled. The internal regulator provides a stable supply for the remaining circuitries. Three events can shut down the IC: EN/DIM remaining low for longer than t_{OFF_DELAY}, V_{IN} going below UVLO, and thermal shutdown. In the shutdown procedure, the signaling path is blocked first to avoid any fault triggering. Then the COMP voltage (V_{COMP}) and the internal supply rail are pulled down.

Error Amplifier (EA)

The internal low offset error amplifier (EA) compares the FB voltage (V_{FB}) with the internal 100mV reference and outputs a COMP voltage (V_{COMP}), which is inside the IC. V_{COMP} is used to control the HS-FET peak current and regulate the output current.

Internal Soft Start (SS)

Soft start (SS) prevents the converter output current from overshooting during start-up. When the MP2341 starts up, the internal circuitry generates an SS voltage (V_{SS}) that ramps up from 0V. The SS period (t_{ss}) lasts until the voltage on the SS capacitor exceeds the 0.1V reference voltage. At this point, the reference voltage (V_{REF}) takes over.

Floating Driver and Bootstrap (BST) Charging

An external bootstrap (BST) capacitor powers the HS floating power MOSFET. This floating driver has its own UVLO protection. The UVLO rising threshold is 2.5V, with a hysteresis of 160mV. The BST capacitor voltage is regulated internally. During normal operation, a 3.3V BST voltage is maintained between BST and SW.

Enable Control (EN/DIM)

The EN/DIM control pin turns the regulator on and off, and dims the output LED current. To turn on the MP2341, leave EN/DIM floating or drive EN/DIM high. The MP2341 turns off after the IC is pulled low for t_{OFF_DELAY} (typically 16ms). Figure 2 shows the control logic for EN/DIM.



Figure 2: EN/DIM Timing Sequence

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

Analog Dimming

The MP2341 provides two analog dimming methods: Apply a DC signal on the EN/DIM pin or send a PWM signal on the PDIM pin.

When the voltage on EN/DIM is below V_{ADIM_MIN}, the LED current is regulated to its minimum scale. When the voltage on EN/DIM is between V_{ADIM_MIN} and V_{ADIM_MAX}, the LED current changes from its minimum scale to its full scale. If the voltage on EN/DIM exceeds V_{ADIM_MAX}, the max LED current is regulated.

Figure 3 shows the analog dimming curve. Due to the EN/DIM on/off threshold hysteresis, at the $V_{EN/DIM}$ falling edge, the chip remains at the minimum LED current until $V_{EN/DIM}$ falls below V_{EN_OFF}. The dimming curve is the same in the linear dimming range.



Figure 3: Analog Dimming Curve by EN/DIM

When a PWM signal is applied to the PDIM pin and the EN/DIM voltage exceeds V_{ADIM_MAX}, the IC dims the LED current with analog mode and the LED current amplitude is equal to I_{SET} x $DUTY_{PDIM}$. (I_{SET} is the LED current set by the resistor connected to the FB pin, and $DUTY_{PDIM}$ is the duty cycle of the PWM signal on the PDIM pin.) Analog dimming helps reduce the LED power loss and avoid audible noise. It is recommended to set the dimming frequency above 10kHz.



Figure 4: Analog Dimming Curve by PDIM

If the EN/DIM voltage is between V_{ADIM_MIN} and V_{ADIM_MAX}, the PWM signal is also applied to the PDIM pin, then the LED current is determined by both effect. In this case, the LED current amplitude is equal to I_{SET1} x $DUTY_{PDIM}$. I_{SET1} is the LED current set by both the resistor connected to the FB pin and the EN/DIM voltage.

PWM Dimming

Apply a PWM signal on EN/DIM to implement PWM dimming mode. To achieve good dimming linearity, the dimming frequency's recommended range is 100Hz to 2kHz. The digital signal's amplitude must be above 1.57V.

Open LED

If the LED is open without an FB signal, the MP2341 works at the max duty cycle and the output voltage rises close to the input voltage.

LED Short-Circuit Protection (SCP)

The MP2341 integrates LED short-circuit protection (SCP) circuitry. Several features protect the MP2341 from damage when an LED short circuit occurs.

The MP2341 features a cycle-by-cycle current limit to restrict the max inductor current. A protection mechanism monitors the FB level though an internal R-C filter. Once it reaches $V_{FB_BURST_TH}$, the IC stops switching until the FB level drops to a lower value; then the system works in burst mode.

In the worst-case scenario, the LED is shorted to ground. If the cycle-by-cycle current limit function cannot clamp the current overshoot sufficiently, the HS-FET and LS-FET currents are also monitored by the over-current detector inside the IC. If the HS current exceeds the

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

OCP current threshold (typically 4A) in every cycle with a 140µs counter, the IC turns off the HS-FET and LS-FET for 2.4ms, then restarts. During this period, V_{COMP} is pulled down to GND for a SS fault condition restart.

Thermal Shutdown

Thermal shutdown is implemented to prevent the MP2341 from operating at exceedingly high temperatures. If the silicon die temperature exceeds 150°C, OTP shuts down the entire IC. When the temperature returns below its lower threshold (typically 130°C), the MP2341 restarts and resumes normal operation.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

APPLICATION INFORMATION

Setting the LED Current

The current-sense resistor is inserted between the anode of LED and GND. The current-sense resistor value can be calculated with Equation (1):

$$R_S = \frac{0.1V}{I_{LED}} \quad (1)$$

For a 2A LED current output, choose R_S = 50mΩ.

Selecting the Inductor

MPL Optimized Performance with MPS Inductor

For most applications, an inductance value below 22µH, with a nominal DC current rating at least 25% higher than the max load current, is recommended. For the highest efficiency, the inductor's DC resistance should be less than 100mΩ. The required inductance value for most designs can be calculated with Equation (2):

$$L = \frac{V_{OUT} \times (V_{IN} - V_{OUT})}{V_{IN} \times \Delta I_L \times f_{SW}} \quad (2)$$

Where ΔI_L is the inductor ripple current.

Choose the inductor ripple current to be 30% of the max load current. The max inductor peak current can be calculated with Equation (3):

$$I_{L(MAX)} = I_{LED} + \frac{\Delta I_L}{2} \quad (3)$$

MPS inductors are optimized and tested for use with our complete line of integrated circuits.

Table 1 lists our power inductor recommendations. Select a part number based on your design requirements.

Table 1: Power Inductor Selection

Part Number	Inductance Value	Manufacturer
MPL-AL family	4.7µH to 15µH	MPS
MPL-AL6060-5R6	5.6µH	MPS
MPL-AL6060-6R8	6.8µH	MPS
MPL-AL6060-100	10µH	MPS
MPL-AL6060-150	15µH	MPS

Visit MonolithicPower.com under Products > Inductors for more information.

Selecting the Input Capacitor

The input capacitor reduces surge current drawn from the input supply and switching noise from the device. The input capacitor impedance at the switching frequency should be less than the source impedance, to prevent the high-frequency switching current from passing through the input. Ceramic capacitors with X5R or X7R dielectrics are highly recommended due to their low ESR and small temperature coefficients. For most applications, a 22µF capacitor is sufficient.

Selecting the Output Capacitor

The output capacitor keeps the output current ripple small and ensures FB loop stability. The output capacitor impedance should be low at the switching frequency. Ceramic capacitors with X5R or X7R dielectrics are recommended for their low ESR characteristics. For most applications, a 10µF ceramic capacitor is sufficient.

Design Example

Table 2 shows a design example following the application guidelines for the specifications.

Table 2: Design Example

V_{IN}	8V to 24V
V_{OUT}	Two WLEDs in series
I_{LED}	2A

Figure 6 shows the detailed application schematic. For the typical performance and circuit waveforms, see the Typical Performance Characteristics section on page 7. For more device applications, refer to the related evaluation board datasheet.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

PCB Layout Guidelines [8]

Efficient PCB layout is critical for stable operation and good EMI performance. For the best results, refer to Figure 5 and follow the guidelines below:

1. Place the input capacitor as close to VIN and GND as possible.
2. Keep the FB trace as short as possible. If the FB length is too long due to component size, an RT resistor is required.
3. Keep the switching noise trace as short as possible.
4. Keep the switch node traces, such as the SW node and BST nodes, short and away from the FB network.

Note:

8) The recommended PCB layout is based on Figure 6.



Figure 5: Recommended PCB Layout

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

TYPICAL APPLICATION CIRCUIT



Figure 6: Typical Buck Converter Application, V_{IN} = 8V to 24V, 2 WLEDs in Series, V_{OUT} = 5.9V, I_{LED} = 2A

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

PACKAGE INFORMATION

SOT583



TOP VIEW



BOTTOM VIEW



FRONT VIEW



SIDE VIEW



RECOMMENDED LAND PATTERN

NOTE:

1) ALL DIMENSIONS ARE IN MILLIMETERS.
2) PACKAGE WIDTH DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSION.
3) LEAD COPLANARITY (BOTTOM OF LEADS AFTER FORMING) SHALL BE 0.10 MILLIMETERS MAX.
4) DRAWING IS NOT TO SCALE.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

CARRIER INFORMATION



Part Number	Package Description	Quantity/Reel	Quantity/Tube	Quantity/Tray	Reel Diameter	Carrier Tape Width	Carrier Tape Pitch
MP2341GTL–Z	SOT583	5000	N/A	N/A	7in	8mm	4mm

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.

Revision History

Revision #	Revision Date	Description	Pages Updated
1.0	10/29/2020	Initial Release	-

NOTICE: The information in this document is subject to change without notice. Users should warrant and guarantee that third-party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.

MPS Proprietary Information. Patent Protected. Unauthorized Photocopy and Duplication Prohibited.
© 2020 MPS. All Rights Reserved.