

EVK75123 REAL-TIME 3D IMAGING TIME-OF-FLIGHT CHIPSET EVALUATION KIT

QVGA TIME-OF-FLIGHT CHIPSET EVALUATION KIT

The EVK75123 is the evaluation kit for the MLX75023 and MLX75123 Time-of-Flight (TOF) chipset. This new chipset enables real-time 3D imaging at full QVGA resolution with unsurpassed sunlight robustness. The evaluation kit is a complete camera built around this chipset and can be directly connected to a PC for visualization and recording of depth map data, while allowing direct access to many configuration settings.

EVK75123 is a modular plug and play platform perfectly set up for customization by its customers. The kit consists of four stacked PCBs (from top to bottom: illumination board, TOF chipset board, interface board and a processor board). It is possible to detach the top two PCBs from the bottom two PCBs by bypassing the board to board connection with an external cable suitable for FPD-Link III communication. A graphical user interface for Windows is provided for live depth map visualization, basic recording, analysis and configuration. For custom SW development, a MATLAB SDK and C API is also provided. The built-in flexibility of our evaluation kit enables any designer to develop the necessary system know-how and experience for use in their application.

The evaluation kit is available in variants with 60 deg and 110 deg field-of-view (FOV).

KEY FEATURES

- MLX75023 and MLX75123 TOF Chipset
- Ø 120 klux sunlight rejection
- ✓ VCSEL illumination (60° or 110°)
- Modulation frequency up to 40MHz
- Oistance and confidence data at max. 60 FPS
- 🧭 Visualizer, C API and Matlab SDK
- ✓ Dimensions: 80 x 50 x 35mm 15mm TOF chipset board only



FOR MORE INFORMATION: WWW.MELEXIS.COM/EVK75123



ILLUMINATION BOARD

- 4x VCSELs (60° or 110° field of view)
- Programmable peak optical power (0 25W)
- Onboard temperature sensor
- Sye safe (certificate available)

TOF CHIPSET BOARD

- MLX75023 QVGA, 320x240 pixels, TOF sensor array
- MLX75123 TOF companion chip
- Standard S mount (M12x0.5) lens holder
- \bigcirc Two temperature sensors
- Programmable input clock and VMIX voltage
- FPD-Link III serializer

INTERFACE BOARD

- Interface between TOF Chipset Board and CM-i.MX6 Board
- SPD-Link III deserializer
- Power input (9 16V) and RJ45 ethernet connector
- ✓ GPIO connector (I²C, SPI, VIN, 3V3 & three GPIOs)

CM-I.MX6 PROCESSOR BOARD

- 🧭 Quad core i.MX6 processor running up to 1.2 GHz
- 🛇 Calculates the distance and confidence data

EVK75123 PACKAGE CONTENTS

- ✓ 1x HW module
- ✓ 1x external AC/DC PSU
- ✓ 1x ethernet cable
- 🛇 Visualizer for Windows
- MATLAB SDK & C API (+ example code)
- Registration number (for SW, documentation & support)

EVK75123 ORDER CODES

- Sev K75123-60-850-1: 60deg FOV, 850nm VCSELs
- EVK75123-110-850-1:
 110deg FOV, 850nm VCSELs
- EVK75123-110-940-1: 110deg FOV, 940nm VCSELs



BLOCK DIAGRAM

The above informations' as is "and believed to be correct and accurate Melevis disclaims any and alliability incorrection with or artificing out of the furnishing, application or used the information or products any and alliability including without initiation, special, consequentiated includental damages and any and allower anties, express, statutory, implied, or by description, including warranties of fitness for particular purpose non-infringement and merchanizability. Melevis reserves the right to chunge it at any time and without notice. Users should obtain the latest vesion of the information or products any and all lability including without includes. The should be applied on a should be applied on the state vesion of the information or products are should obtain the latest vesion of the information to verify and export and the applications, such as a product are and any and allower and the applications require guidents and applications require applications require applications requires an and any and applications applications applications and applications and applications and applications applications and applications are applications applications applications applications and applications and applications applicating applications applicating applicating applications applic