

837-P



Water Soluble Flux Pen

Our Water Soluble Flux Pen contains a water-soluble soldering flux. The flux has a neutral pH at room temperature and becomes highly activated at soldering temperatures. Post-soldering flux residues must be cleaned, but are easily removed with water.

The 837-P is an ideal flux pen for rework. It is designed for the prototyping, rework and repair of conventional and surface mount circuit boards.

Features & Benefits

- Meets IPC J-STD-004B and type ORL0
- For both leaded and lead-free solders
- Chiseled tip allows precise application
- Rosin/resin free
- Halogen-free
- RoHS compliant

Available Packaging

| Cat. No. | Packaging | Net Vol. | Net Wt. |
|----------|-----------|----------|---------|
| 837-P | Pen | 10 mL | 8.46 g |

Contact Information

MG Chemicals, 1210 Corporate Drive
Burlington, Ontario, Canada L7L 5R6

Email: support@mgchemicals.com

Phone: North America: +(1)800-340-0772

International: +(1) 905-331-1396

Europe: +(44)1663 362888



Properties

| | |
|-----------------------|---------------------------------|
| Flux Classification | ORH1 |
| Flux Type | Organic |
| Flux Activity | High |
| Halides by Weight | 2.2% ±0.3% |
| Copper Mirror | Complete removal of copper film |
| Corrosion | Pass |
| Cleaning Requirements | Required |
| Solid Percentage | 17.5% ±1% |

Application Instructions

Read the product SDS before using this product (downloadable at www.mgchemicals.com).

1. Depress the tip against a hard surface until the felt tip gets wet, but not flooding.
2. Gently brush the wet tip onto the soldering area to apply. To keep the tip saturated and control the flow, only press in the tip as needed.
3. Clean residue with water.

Storage and Handling

Store between 18 and 27 °C in a dry area, away from sunlight (see SDS).

Disclaimer

This information is believed to be accurate. It is intended for professional end-users who have the skills required to evaluate and use the data properly. M.G. Chemicals Ltd. does not guarantee the accuracy of the data and assumes no liability in connection with damages incurred while using it.