Weller

WHA3000PN

Hot air station 110 V Product no.: WHA3000PN



Benefits

- > Hot Air Station With Internal Pump
- Suitable for repairs of fine-pitch components with a large no. of leads
- > The hot air pencil has vacuum pickup for easy component removal
- The vacuum pickup feature is activated automatically during the process
- > Temperature and air flow are controlled independently
- Controlled output maintains set temp regardless of air flow setting



Dimensions L x W x H (mm)	240 x 270 x 170 mm (9,44 x 10,63 x 6,69 inch)
	240 X 270 X 170 Hilli (5,44 X 10,05 X 0,05 Hich)
Dimensions L x W x H (inches)	
Weight (approx.) in kg	
Voltage	120 V
Power	600 W
Channels	
Temperature range (depends on tool) °C	50 - 550
Temperature range (depends on tool) °F	122 - 1022
Temperature accuracy °C	± 30 °C (± 54 °F)
Temperature accuracy °F	
Temperature stability °C	
Temperature stability °F	
Equipotential bonding socket	
Display	
Air consumption l/min	5 - 50 l / min
Operating pressure in bar/psi	
Capacity l/min	
Vacuum	-0,6 bar

Phone: +49 (0) 7143 / 580-0 Fax.: +49 (0) 7143 / 580-108 Email: info@weller-tools.com

Web: www.weller-tools.com