









PB-7

Designed for use on relay contacts, this pocket burnisher is the perfect tool for removing the oxide layer from the precious metals of relay contacts. These burnishers feature the following:

- Blade length and rigidity is adjustable by varying the depth of the blade in the chuck
- Plastic housing allows it to be used on live contacts without any shocks or shorts
- Removes the oxide layer or corrosion off contacts without leaving filings or debris

PB-3 Includes (6) Flat 0.0035" Blades, stored in the opposite end of the pen

PB-3R Includes (6) Flat 0.0035" Blades and (6) 0.020" diameter Rods, stored in the opposite end of the pen

PB-7 Includes (6) Flat 0.007" Blades, stored in the opposite end of the pen

SPECIFICATIONS	PB-3	PB-3R	PB-7
BLADE TYPE	Flat	Flat & Round	Flat
BLADE THICKNESS	0.0035" (0.089mm)	0.0035" (0.089 mm)	0.007" (0.018 mm)
BLADE WIDTH	3/16" (4.76 mm)	3/16" (4.76 mm)	3/16" (4.76 mm)
BLADE LENGTH	1 1/2" (38.10 mm)	1 1/2" (38.10 mm)	1 1/2" (38.10 mm)
PEN LENGTH	4 1/2" (114.3 mm)	4 1/2" (114.3 mm)	4 1/2" (114.3 mm)
PEN DIAMETER	3/8" (9.53 mm)	3/8" (9.525 mm)	3/8" (9.53 mm)
WEIGHT	0.068 lb (30.85 g)	0.069 lb (31.30 g)	0.069 lb (31.30 g)
UPC #	811490014398	811490014404	811490014411

