Fair-Rite Products Corp.
Your Signal Solution®

PQ Cores (6695272521)

Part Number: 6695272521

95 PQ CORE SET

PQ cores were developed for use in power applications. The large surface area to volume of the core aids in heat dissipation. PQ cores are employed both in filter and transformer designs for switch mode power supplies.

 PQ cores can be supplied with the centerpost gapped to a mechanical dimension or an A_L value.

Catalog Drawing
3D Model

Weight indicated is per pair or set.

Weight: 36 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	26.5	± 0.50	1.043	_
B	12.5	± 0.15	0.492	_
C	19	± 0.40	0.748	_
D	8.05	± 0.15	0.317	_
E	22.5	± 0.40	0.886	_
F	12	± 0.30	0.472	_
G	15.5	min	0.611	min




Chart Legend
Σl/ A : Core Constant, l_e : Effective Path Length, A_e : Effective Cross- Sectional Area, V_e : Effective Core Volume
A_L : Inductance Factor
Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
A_L(nH)	6000 ±25%
Ae(cm^2)	1.177
Σl/ A(cm^{-1})	4.59
l_e(cm)	5.4
V_e(cm^3)	6.359
A_{min}(cm^2)	1.131

A_L value is measured at 1 kHz, B < 10 gauss.

Fair- Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • • www.fair- rite.com